

Specifications PowerLink WPS45S-AU Generator

Date of Manufacture	01/05/020
Prime Rating kVA	45
Make	Powerlink
Model	WPS45S-AU
Serial No.	SAU0114/272
Engine Make	Perkins
Engine model	1103A-33TG1
Engine serial	DK83398*S027583F
Current Engine Hours	16,952
Cylinders	3
Governor	Mechanical
RPM	1500
Service hours	400
Air filter	AF25526
Fuel filter 2	4461492
Oil filter full flow	LF701
Oil capacity	8 Litres
Coolant capacity	10 Litres
Starter Motor 12/24v	Perkins T400267 12V
DC Alternator 12/24v	Perkins 65A 12V 2871A306
Fan belt	13A1330
Alternator model	Leroy Somer LSA42.3M7 J 6/4
Alternator serial	73566 009
AVR	R220
Control panel	DeepSea 7420
Outlets Fitted	2x32A + 1x15A
Battery	1 x Delkor NX110-5LMF
Fuel Type	DIESEL
Fuel cons @ 75%	8l/hr
Fuel capacity	270 Litres
Avge noise @ 7m	67 db(a)
Length	2338mm
Width	1180mm
Height	1701mm
Approx wet weight	1770kgs